


## Operation instruction of VEWsmart APP Smart Downlight

### Step 1: Download the "VEWsmart" APP

You can download the VEWsmart app by searching for VEWsmart in your app store or by scanning the following QR code



### Step 2: Registration / Log in

- 1). Enter your mobile phone number or email address and tap Get Verification Code. The country or region on the registration page is the same as that you set in the mobile phone. You can also manually change the country or region before registration.
- 2). On the Enter Verification Code page, enter the verification code. On the Set Password page, set the password as per instructions and tap Done.
- 3). Enter your registered mobile phone number or email address, enter the pass-word, and then tap Log In.


### Step 3: Manually add Wi-Fi+Bluetooth dual-mode devices

1. If you use a Wi-Fi+Bluetooth dual-mode product, power on the device first. Then, enable Bluetooth on your mobile phone and open the app. Bluetooth and Wi-Fi+Bluetooth dual-mode devices that are ready for pairing will be displayed.
2. Select the device to be added. On the Wi-Fi setting page, enter the password for connecting to the 2.4 GHz Wi-Fi network. Wait for the device to automatically complete pairing.

### Step 4: Add Device

- 1). Switch on-off-on-off-on, the lamp will be flickering
- 2). Click "add device" on the home page of the Tuya APP (as following), you will find a lamp, click to enter, you can control the lamp via cell phone directly.

### Step 5: Control Lamp:


Touch the bottom  Lamp will be turned on. Touch the bottom again, Lamp will be turned off.

a. CCT Changeable Function:



to adjust any colour temperature you required

b. Dimming Function:



to adjust any brightness you required

c. Memory Function:

Turn off the lamp, and when you turn on the lamp again next time, it will keep the same color temperature & brightness as the state before.

d. Timer Function:

You can set the lamp to turn on or off at any time you required

e. Countdown Function:

You can set the lamp to turn on or off after a specific time

f. Share Function:

You can share the device with others to control the lamp together.

g. Group control Function:

- 1). Tap Create Group on the management page of a selected device.
- 2). On the Select Device page, select devices that you want to add to the control group and tap Save. Enter a group name, and tap Confirm. The Select Device page shows all devices of the same model as the selected device.
- 3). When the group is created, the app automatically displays the group control panel, where you can control devices in groups.

### Additional features

- Third-Party Voice Services  
On the page of me, click more of Third-Party Voice Services, you can achieve voice control with Smart Speakers such as Amazon Alexa, Google Home, SmartThings etc according to the instructions inside




- Family Management  
You can tap Home Management to manage your homes and home members.

### IP65 Fire Rated Downlight - Installation and Operation Manual

#### Specifications

Part number	<b>K05-6085-WI</b>
Dimensions	Cutout 65mm Dia 90mm x 38mm
Rated voltage	220-240V
Power Output	8w
Colour	2700-6000K
Lumens	8w 640-760Lm
IP Rating	IP65
Dimming	Smart Dimmable
Beam	60°
Fire Rated	Up to 90 mins



#### Important Safety Information

- Turn off and isolate the electrical supply before connecting this fitting to the building wires.
- Must be installed or connected by a licensed electrician.
- The luminaries are intended for indoor use only.

#### Installation

